



# JOHNSON/EVINRUDE Application Guide



Application Guide									
<b>OMC (SeaDrive) Application Guide</b>									
HP	Model	Year#	Cyl	Power Pack & Limit	Stator	Rect/Reg	Trigger	Harness	Ign Coil
<b>Sea Drive</b>									
2.5 L	-	82	6	113-2138 CD3/6 NO LIMIT	173-3672	153-3408	133-3377	413-9452	183-2366
2.6 L	-	82	6	113-2138 CD3/6 NO LIMIT	173-3672	153-3408	133-3377	413-9452	183-2366
1.6 L	-	83	8	113-2125 CD4/8 NO LIMIT	173-3672	153-3408	133-3376	R393290*	183-2366
2.6 L	1AA/2BA/2BB 10Amp	83	6	113-2556 CD3/6 5800 L	173-3672	153-3408	133-3377	R582586*	183-2366
2.6L	1AA/2BA/2BB, 35Amp	83	6	113-2138 CD3/6 NO LIMIT	173-3668	193-5204	133-3377	R393603*	183-2366
1.6 L	S V4	84	4	113-2125 CD4/8 NO LIMIT	173-3672	193-5204	133-3376	413-4495	183-2366
2.5 L	-	84	6	113-2556 CD3/6 5800 L	173-3668	193-5204	133-3377	413-2866	183-2366
2.6 L	-	84	6	113-2556 CD3/6 5800 L	173-3668	193-5204	133-3377	413-2866	183-2366
1.6 L	-	85	4	113-2811 CD4/8 NO LIMIT	173-3672	193-5204	133-3376	413-5253	183-2508
2.5 L	-	85	6	113-2651 CD3/6 AL 5800	173-3668	193-5204	133-3377	413-2915	183-2508
2.6 L	-	85	6	113-2651 CD3/6 AL 5800	173-3668	193-5204	133-3377	413-2915	183-2508
1.6 L	-	86	4	113-3110 CD4/8 NO LIMIT	173-3104	193-5204	133-3376	413-3036	183-2508
2.6 L	-	86	6	113-3114 CD3/6 5800 L	173-3668	193-3689	133-3377	413-3035	183-2508
1.6 L	-	87	4	113-3110 CD4/8 NO LIMIT	173-3104	193-5204	133-3376	413-3036	183-2508
1.8 L	-	87	4	113-3101 CD4/8 AL 6100	173-4291	193-3689	133-3379	R583135*	183-2508
2.7 L	-	87	6	113-3605 CD3/6 AL 6200	173-3668	193-3689	133-3048	R583179*	183-2508
3.6 L	-	87	8	113-3101 CD4/8 AL 6100	173-3117	193-3689	R583148*	R583181*	183-2508
1.6 L	-	88	4	113-3101 CD4/8 AL 6100	173-3536	193-4204	133-3379	R583596*	183-2508
2.0 L	-	88	4	113-4041 CD4AL 6700 L	173-4288	193-3689	133-3508	413-4406	183-2508
3.0 L	-	88	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	R583597*	183-2508
1.6 L	-	89	4	113-4030 CD4/8 5800 L	173-3536	193-4204	133-3379	413-4004	183-2508
2.0 L	-	89	4	113-4041 CD4AL 6700 L	173-4288	193-3689	133-3508	413-4406	183-2508
3.0 L	-	89	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	R583597*	183-2508
4.0 L	-	89	8	113-4035 CD8AL 6700 L	173-4287	193-3689	R583531*	R583598*	183-2508
1.6 L	-	90	4	113-4028 CD4/8 NO LIMIT	173-3536	193-4204	133-3379	R986537*	183-2508
2.0 L	-	90	4	113-4041 CD4AL 6700 L	173-4288	193-3689	133-3508	413-4406	183-2508
3.0 L	-	90	6	113-4037 CD6AL 6700 L	173-4287	193-3689	133-3533	R583597*	183-2508
4.0 L	-	90	8	113-4035 CD8AL 6700 L	173-4287	193-3689	R583531*	R583598*	183-2508
<b>Battery CD Ignition Systems</b>									
HP	YEAR	CD. IGN	TYPE	STATOR	IGN. COIL	SENSOR		REG/RECT	
55	'68-'69	113-7123	6CB2007	173-0726 <sup>9</sup>	183-2382	Points		153-0705	
60	'70-'71	113-7123	6CB2001	173-0744 <sup>9</sup>	183-2382	Points		153-3408	
65-85	68	113-7123	6CB2009	173-0726 <sup>9</sup>	183-2382	Points		153-0705	
85	'69-'72	113-7123	6CB2004	173-0744 <sup>9</sup>	183-2382	Points		153-3408	
100	'67	113-8362	IDG3001A	R580648 <sup>15</sup>	183-2382	*R580668		153-3408	
100	'68	113-8362	IDG3001B	173-0725 <sup>15</sup>	183-2382	133-5008		153-3408	
100	'71	113-7123	6CB2004	173-0744 <sup>9</sup>	183-2382	Points		153-3408	
100	'72	113-8362	IDG3001	173-0744 <sup>9</sup>	183-2382	133-5008		153-3408	
115	'69-'70	113-8362	IDG3001C	173-0744 <sup>9</sup>	183-2382	133-5008		153-3408	
125	'71-'72	113-8362	IDG3001	173-0744 <sup>9</sup>	183-2382	133-5008		153-3408	
<b>Power Pack Type Ignitions (Terminal Block)</b>									
50-55	'71-'77	113-1397	PP2	173-1232 <sup>6</sup>	183-2091	133-0875K1		153-3408	
65-75	'72-'78	113-1726	PP3	173-1235 <sup>6</sup>	183-2303	133-1251		153-3408	
85-140(V-4)	'73-'77	113-1731	PP4	173-1225 <sup>6</sup>	183-4632	133-1900		153-3408	
150-200(V-6)	'76-'77	113-1726	PP3/6	173-1867 <sup>9</sup>	183-2303	Points		153-3408	
<b>CD Type Ignitions 1977-1984 (Non-Limited)</b>									
6-35	'77-'84	113-2453	CD2	173-1651 (E) 173-1670 (coil only)	183-2366	In Stator 133-3387 (Manual St)		153-1778 N/A	
50-60	'78-'84	113-2453	CD2	173-1651 <sup>5</sup>	183-2366	In Stator		153-1778	
40-60	'83-'84	113-2453	CD2	173-1670 (coil only)	183-2366	133-3387		153-1778	
70-75	'79-'84	113-2138	CD3/6	173-3724 <sup>9</sup>	183-2366	133-3387		153-3408	
85-90-100- 115-140 (V4)	'78-'84	113-2125	CD4	173-3672 <sup>9</sup>	183-2366	133-3376		153-3408	
150- 235	'79-'84	113-2138	CD3/6	173-3672 <sup>9</sup> 173-3668 <sup>35</sup>	183-2366	133-3377		193-5204	

(a) = 3/8" Linkage Hole (E) = Electric Start (CHG) = Charging R&R = Repair and Return \* = Repair and Return  
 (b) = 1/2" Ball Socket (M) = Manual Start Not Appl. = Not required part \*\* = Not available from CDI Electronics